

RF Wireless Remote Control Radio Controller / Transmitter & Receiver

Package Include:

1 x Receiver: S1FS-DC12 (1 Channel / Speed Adjustable)
2 x Transmitter: CWC-3
1 x User manual

Features:

Wireless control, easy to install
Control 1 motor to rotate with the transmitter (remote control) from any place within a reliable distance.
Wireless signal can pass through walls, floors and doors.
Two speed control buttons on the remote to adjust the speed of motor separately.
Reliable control: The transmitter (Encoding) and the receiver (Decoding) use an 8-bit code.
One/several transmitters can control one/several receivers simultaneously.
If you use two or more receivers in the same place, you can set them with different codes.
Transmitting Frequency: 433MHz

Receiver:

Model No.: S1FS-DC12
Coding Type: Fixed code
Input/output Voltage: DC 12V~24V
Maximum Working Current: 20A
Case size: 60mm x 50mm x 20mm
Weight: 70g

Transmitter:

Model No.: CWC-3
Channel: 3 CH
Remote Control Distance: 50m / 150ft (theoretically)
Encode: Fixed code by soldering
Unit Size: 58mm x 30mm x 12mm
Power Supply: 1 x 23A -12V battery (included, can be used for 12 months)

Usage:

Connect terminals “+” and “-” to power supply DC12V~24V; connect terminals “A” and “B” to motor.
Press button ● on remote: motor rotates
Press button ● again: motor stop rotating

Speed of motor can be adjusted by the buttons:

Press button ▲ on remote, the speed will be faster.
Press button ▼ on remote, the speed will be slower.

