

1 Button 100M RF Remote Control / Transmitter With Sliding Cover

Product Description:

Model No.: 0021000 (C-1)

With Sliding Cover: Slide up when it doesn't work (to protect the button). Slide down the button will appear.

Shell Color: Wood Color / White

Channel/Button: 1

Button Symbol: no symbol

Operating Voltage: 12V (1 x 23A -12V battery, can be used for 12 months)

Operating Current: 6mA

Operating Frequency: 315Mhz / 433Mhz

Encoding Chip: PT2262 / PT2264 / SC2262

Encoding Type: Fixed code by soldering, up to 6561 codes

Transmitting Distance: 100m / 300ft (theoretically)

The distance of 100m is a theoretical data, it shall be operated in an open ground, no barriers, no any interference. But in the practice, it will be hindered by trees, walls or other constructions, and will be exposed to some interference by other signals. Therefore, the actual distance may or may not reach 100m.

If you stretches the telescopic antenna, it can have a further working range, which is twice as much as it used to be.

Modulation Mode: ASK

Operating Temperature: -20 ° C to +70 ° C

Unit Size: 58mm x 39mm x 16mm

Weight: 30g

Uses: garage doors, motorcycles, car alarm products, home security products, wireless remote control products, industrial control products.

How to set up the 8-bits code of the transmitter:

1. Open the transmitter shell, then you will see the circuit board. There are two rows pads and one row of chip feet on the back side.
2. The upper row of pads is "L" side, and the lower row of pads is "H" side.
3. If solder the middle row of chip feet to the "L" side, it is code 1. If solder the middle row of chip feet to the "H" side, it is code 2. Don't solder to any side, it is code 0.
4. The 8-bits code order is from left to right (from D1 to D8).
5. Here is an example, the 8-bits code in the picture is 01121101, solder as the following way:
6. Code 0: don't solder any side, like D1 and D7.
7. Code 1: solder to the "L" side, like D2, D3, D5, D6, D8.
8. Code 2: solder to the "H" side, like D4.

