

AC 110V or 220V or 380V Contactor Motor Starter Relay 3-Phase Pole 18A

Feature:

ABS flame retardant plastics

AC contactor (aka motor starter) is a high capacity relay. It is often used to control a motor or as a main power switch.

It's used for long range connection and circuit disconnection, frequent activation and controlling AC motor.

Specification:

Model No.: 0040010

Three main contact: All Normally Open

One auxiliary contact: Normally Open

Contact: Silver

Max. Current: 18A

Contact Rating: 220V/18A/4KW, 380V/18A/7.5KW, 690V/18A/10KW

Control (Coil) Voltage: 110VAC, or 220VAC, or 380VAC (You must specify the coil voltage. Otherwise, 220V coil will be sent out as default choice)

Weight: 370g

Dimensions: 47mm x 76mm x 87mm

Mounting Method: 35mm DIN Rail or Screw On.