

1 Button Free Sticker Wireless Calling Button / Transmitter

Remote control calling system is the hi-tech electronic product which is integrated wireless communication and computer technology. It includes calling button and calling receiver. Each system has one calling receiver and many calling buttons. When there is a calling from a calling button, calling receiver will display corresponding number.

It is widely applied to restaurants, coffee shops, karaoke rooms, discos, sauna rooms, beer houses, pubs, night clubs, bowling alleys, golf courses, video halls, hotels, hospitals, schools, chain stores ,shops...

Package Include:

- 1×Wireless Calling Button
- 2×CR2032 batteries
- 2×Double-sided adhesive tapes

Product Description:

Model No.: 0021201

Shell Color: White

Channel/Button: 1

Button Symbol: Call

Operating Voltage: 6V(CR2032×2)

Operating Current: 6mA±3mA

Operating Frequency: 433.92Mhz

Encoding Chip: EV1527

Encoding Type: Learning code (up to 1 million codes, reducing code collision and unauthorized code scanning possibilities.)

Transmitting Distance: 200m / 600ft (theoretically)

The distance of 200m is a theoretical data, it shall be operated in an open ground, no barriers, no any interference. But in the practice, it will be hindered by trees, walls or other constructions, and will be exposed to some interference by other signals. Therefore, the actual distance may or may not reach 200m.

Modulation Mode: ASK

Operating Temperature: -20 ° C to +70 ° C

Unit Size: 86mm x 86mm x 10mm

Weight: 60g

Case Material: Plastic

This transmitter can work with different kinds of receivers, include model 0020043 (S1U-DC12), 0020330 (S1U-AC220), 0020046 (S1PU-DC12), 0020275 (S1PU-AC220), 0020610 (S1RU-DC12), etc.

Uses: garage doors, motorcycles, car alarm products, home security products, wireless remote control products, industrial control products.

Usage:

Stick the calling button to wall or desk. When you press its button, the calling receiver will display the corresponding number and make sounds.