


DC 12V~50V Motor Speed Adjustment Switch/ Speed Governor

Feature:

- Model: 0044005
- Voltage: DC 12V~50V
- Rated current: 30A
- Unit Size of Controller: 112mm x 78mm x 36mm
- With 30A fuse
- Speed Adjustment Range: 0%~100%.
- Adjustable potentiometer: 100K
- The speed of motor rotation can be adjusted according to 0~100% through twisting the “Adjustable potentiometer”, then the digital screen will display digital 0~100. That means when the screen display digital “0”, the motor stop rotating; when the screen display digital “1 ~100”, the motor rotating. The higher the number, the faster rotation. When the screen display digital “100”, that means the speed of motor rotation is fastest.

Speed adjustment:

- You can twist “Adjustable potentiometer” to adjust the speed of motor rotates in positive / reversal direction. Twist clockwise, motor rotation will speed up; Twist anti-clockwise, motor rotation will slow down.



Usage:

- Connect DC power wire to the terminal “Input”. Connect the DC motor to the terminal “Output”.
- Twist the “Adjustable potentiometer”, adjust the speed of motor rotation. Twist clockwise, motor rotation will speed up; Twist anti-clockwise, motor rotation will slow down.

